

17.78cm (7)

Color TFT LCD Display



Features

- 17.78cm (7) TFT-LCD digital touch screen, can monitor entrance, outdoor situation anytime and
- work with a door camera for a second calling.
- Remote unlocking
- Directly call can talk with center unit, and send alarm information.
- Call any other indoor unit in LAN system
- Download chord ring tones and setup mute status.
- Call elevator function
- Resident custody
- Household appliance control
- Support voice, pictures, message checking function
- Accept service from center unit
- Max 4 indoor units work together
- Support remote upgrading function.

Specification

Model	S-7LCD
LCD	17.78cm (7) TFT-LCD
Input voltage	DC18V
Sensitivity	20mV
Distortion	5%
Display Pixel	384000dots
Working Current	350mA ± 20%
Standby current	200 mA ± 20%
Output power	50mW
Display time	About 85 ~ 180 S
Network port	RJ45
Network transmission mode	TCP/IP
Transmission range	Router or PBX less than 100m, FOT more than 100
Working Humidity	45% ~ 95%
Storage temperature	- 15°C ~ 55°C

IP Villa Intercom Indoor Station

