



Model No: S-MRK

Features

- Latest fashion, beautifully designed
- Built-in transceiver antenna
- Built-in Keypad
- Less than 100ms decoding time
- Low power dissipation with wide range single power supply
- Support Wiegand26 and RS485 interface
- Built-in LED and buzzer

Interface Description

	Description
Output Interface	Standard Wiegand26, RS485 (Optional Wiegand 34)
Operating Frequency	13.56MHz
Card Reading	Mifre
Transmitting Distance	WG<100M,RS485<1200m
Read Range	Upto 50mm
Power	DC6~14V
LED	Built-in LED
Keypabd	Yes, 12 Keys Operation
Buzzer	Built-in
Color	Black
Material	PVC Case Material
Operating Current	120mA
Temperature	-20°C~60°C
Relative Humidity	10%-90%

Mifare / Smart Card Reader w Keypad

